

# Datasheet

## CONNEXOON



Connected Environments (Connexoon RTS)	
<b>First Step</b>	Accelerate even more connectivity in homes by proposing to users and to professionals a simple, attractive and accessible offer to connect Somfy's equipments. Connexoon, a smooth first step, into Somfy Connect universe
	My house welcomes me: thanks to geofencing, gate and garage door open just before I come home. Outdoor lights automatically turn on at night. All equipment close as soon as my car is parked.
	When you leave your home, in 1 click on your Smartphone, close your roller shutters and activate your alarm.



Installation	
1	
2	
3	
4	

Technical Specifications	
<b>Protocol / Frequency</b>	RTS (433Mhz)
<b>Radio range</b>	200m free field 20m through 2 concrete walls
<b>Dimensions (lxPxx)</b>	110 x 71,5 x 24 mm
<b>Weight</b>	≈77gr
<b>Power</b>	μUSB 5VDC / 500mA Power supply 110/230V- 50/60 Hz (E/F/J Type compliant)
<b>Consumption</b>	120 mA (nominal)
<b>Connectors</b>	1x Ethernet RJ45 1x Micro-USB
<b>Operating ambient temperature</b>	+5°C to +35°C
<b>Color</b>	White
<b>Others</b>	LED (Red/Green) "Select" button "PROG" button "Reset" button
<b>In the box</b>	1x USB power adapter 1x RJ45 cable 1m 2x Quick start guides 1x Legal notice

CONNEXOON  
ACCESS

CONNEXOON  
WINDOW

## CONNEXOON



Category	Type	Max
Pairing	RTS Channels	24 + 6 (Select/Prog)
	Equipment per Channel	1
	HUE Bridges	1 (50 lamps)
System	Actuators in "Ambiance/Mode"	20
	Actuators in a Timer	20
	Timer	8
	Users (smartphones) per account	4



CONNEXOON  
ACCESS

CONNEXOON  
WINDOW

\*\* "I come back" and "I leave" modes from Access app stand for 2 modes each

\*\* The amount of modes used by all users on all apps cannot exceeds 40